

DEG. DIV.	ANGLE			
	A	B	C	D
0~5	±0.02	±0.05	±0.1	±0.2
5~10	±0.05	±0.1	±0.15	±0.5
10~50	±0.1	±0.15	±0.2	±0.5
50~500	±0.15	±0.2	±0.25	±0.5
500~	±0.15%	±0.2%	±0.25%	±1.0

版次	修改内容	修改	审核	批准	日期
V0.1	第一次发行				

Shenzhen ORVIBO Technology Co., Ltd.
7F, Building A1, Nanshan Hi-Tech Industrial, No.1031
Nanshan Avenue, Nanshan District, Shenzhen, China
518055, PRC
support.us@orvibo.com www.orvibo.com

Any help needed, please contact us by
support.us@orvibo.com

Product Description

ORVIBO Smart Wi-Fi Switches can quickly replace traditional single-pole switches, enabling remote control from anywhere with your smart phone app. You could create the automation for the switch by setting the timer schedules, sunrise/sunset, or together with compatible ORVIBO smart home products.

It adopts a Wi-Fi communication protocol and also can work with Amazon Alexa, Google Assistant, and Siri's voice. The switch is for indoor use only. The neutral wire is required. It works with single-pole switches, not with 3-way switches or dimmer switches. The Remote Switch is a portable control switch. It can control the Smart Wi-Fi Switch, no batteries would be required during use.

Contents

- Packing List 03
- Specification 04
- Installation - A10 Smart Wi-Fi Switch 06
- Installation - EU1254 Remote Switch 13
- Download App and Register 19
- Add Device and Configuration 20
- Utilize the App Feature 21
- Voice Control Via Siri 26
- Support Amazon Alexa and Google Home 27
- FAQ 28
- Warranty Coverage 29
- FDCC 31

Packing List

- Smart Wi-Fi Switch x1
- Base Plate x1
- Remote Switch x1
- Bracket x2
- Logo Sticker x1
- User Manual x1
- Wire Connector x4
- Double Sided Tape x1
- Screw x4
- Screw x4

Specification

Product Model	A10
Product Size	4.21*1.29*1.61 in.
Operating Voltage	100-240V / 50/60Hz
Load Range	500W/100 200W LED or CFL
Wireless Type	2.4GHz Wi-Fi & ZigBee 4.0
Working Temperature	32°F~122°F
Working Humidity	<90%RH (Non-condensing)

Specification

Product Model	EU1254
Product Size	2.89*1.91*0.63 in.
Operating Voltage	Self-powered DC3.3V
Wireless Type	433MHz RF
Working Temperature	32°F~122°F
Working Humidity	<90%RH (Non-condensing)

Installation - A10 Smart Wi-Fi Switch

- Turn off the power at circuit breaker
- Uncover the switch from the wall
- Identify and label the wires

4. Remove the existing switch.
Make sure the circuit breaker is power off. Disconnect all wires from the switch.

5. Connect the Smart Wi-Fi Switch from the switch.

Make sure the circuit breaker is power off. Use wire connector connect the wires on the Smart Wi-Fi Switch to the labeled wires coming from the wall in order:

- Connect Neutral wires to N wire of the switch
- Connect Ground wires to G wire of the switch
- Connect Line wires to L wire of the switch
- Connect Load wires to Load wire of the switch

6. Mount the switch and wallplate.
Use the screws provided.

Installation - EU1254 Remote Switch

- Mount the switch on the wallplate.
- Attach back panel of the bracket to the switch using the screws.
- Snap on the wallplate.

2. Placed anywhere with double sided tape.

Control Instruction

The Remote Switch can control the Smart Wi-Fi Switch, one or multiple at one time. At the same time, multiple Remote Switches can control one Smart Wi-Fi Switch, but the number of Remote Switches could not be more than 10.

Matching Mode

- Press the button for 10 seconds until the indicator light flashes blue.
- Press any button on the remote switch once.

3. The light is off to indicate a successful pairing.

Download App and Register

Download the ORVIBO Home App

- Scan the QR code to download the ORVIBO Home App.
- Go to the App Store or Google Play to download the ORVIBO Home App.

Add Device and Configuration

Add Devices Automatically

- Launch the ORVIBO Home App.
- Turn power on at circuit breaker.
- If the indicator light flashes white slowly, you can add devices automatically, and use the ORVIBO Home App to complete all remaining steps.

Add Devices Manually

If the indicator light does not flash white slowly, you need add devices automatically.

- Tap on "+" at the upper right corner at the Home page of the App.
- Tap on "Scan QR code to add device".
- Scan the QR code.

Utilize the App Feature

Control the Light

Set Timer

Long press 2 seconds for setting mode. There are three functions on this screen. You can edit the schedule by setting the time, sunrise, sunset.

Set Countdown

Long press 2 seconds for setting mode. You can create a new countdown.

Set Holiday Mode

Long press 2 seconds for setting mode. You can start the Holiday Mode, and the device will be randomly turned on or off within the set time.

Create Scenes

Smart scene control allows you to control multiple devices together at one touch via voice command or a scene timer.

- Go to the scene page and tap "+" to create a new scene.
- Complete the new scene setting.

Voice Control Via Siri

You can enable Siri voice control with Apple devices. Siri Shortcuts

Go to "Me" > "Find Siri Shortcuts" > "Add to Siri" to customize your voice control from your Apple devices to Home Appliances.

Support Amazon Alexa and Google Home

- Link ORVIBO to Amazon Alexa/Google Assistant
- Control by Amazon Alexa/Google Assistant

FAQ

- The light is not ON.
- How to reset the device?
- Why does the lamp appear dim or flickering?
- Why can't find the switch when add it?

Warranty Range And Duration

One year warranty applies to most ORVIBO products unless specified at the time of purchase. Accessories included with the main device and batteries have a warranty of six months when buying ORVIBO products, the product warranty remains measured from the time it was bought by the original owner.

FCC

FCC Statement

This device complies with part 15 of the FCC Rules. Operation is subject to the condition that this device does not cause harmful interference.

- 备注:
1. 材质: 120g双哑粉纸
 2. 尺寸: 120*80(mm)
 3. 印刷: 四色双面印刷
 4. 装订要求: 骑马钉
 5. 边框线为折痕线, 无需印刷

未注公差: ≤10mm ±0.05mm ≤50mm ±0.1mm >50mm ±0.2mm 单位 mm	制图	审核	批准	产品名称	北美开关套装 说明书	材料	
	鲁枫叶			产品料号	3.06.010831	版次	V0.5
日期	20220310	<p>TEL:+86-0755-85277097 FAX:+86-0755-85277087</p> <p>深圳市欧瑞博科技股份有限公司 SHENZHEN ORVIBO TECH CO.,LTD.</p>					